

TP-LINK CAP

1.4 WNAM TP-LINK CAP (AC500, AC50) CAP. , EAP, Wi-Fi .

WNAM 172.16.130.5 (8080), RADIUS- FreeRADIUS 172.16.130.13. .

RADIUS-. "Authentification" "Radius Server" RADIUS-, , .

tp-link

AC50
Wireless Controller

Save Config

Logout

Status

Network

AP Control

Radio

Wireless

Authentication

- MAC Authentication
- Portal Authentication
- User Management
- Authentication Server

Link Backup

System Tools

Authentication Server

Radius Server

Radius Server

?

+ Add

- Delete

🔍 Search

☐	ID	Name	Address	Authentication Port	Billing Port	Authentication Type	Operation
--	1	wnam	172.16.130.13	1812	1813	PAP	---

Server Name:

wnam

(1-50 characters)

Server Address:

172.16.130.13

(IP Address or Domain name, 1-250 characters)

Authentication Port:

1812

(1024-65535)

Billing Port:

1813

(0, 1024-65535)

Share Key:

secret

(1-120 characters)

Retry Count:

3

(0-10)

Timeout Interval:

3

(1-60 seconds)

NAS IP Address:

(Optional)

Authentication Type:

PAP

▼

OK

Cancel

"Share key" , `/etc/freeradius/clients.conf`. "".

- RADIUS (wnam) "Main Server".

tp-link

AC50
Wireless Controller

Save Config

Logout

Status

Network

AP Control

Radio

Wireless

Authentication

- MAC Authentication
- Portal Authentication
- User Management
- Authentication Server

Link Backup

System Tools

Authentication Server

Radius Server

Authentication Server Group

?

+ Add

- Delete

🔍 Search

☐	ID	Group Name	Authentication Type	Description	Operation
--	1	WnamG	RADIUS	---	---

Group Name:

WnamG

(1-50 characters)

Authentication Type:

☒ RADIUS

Main Server:

wnam

▼

Standby Server:

▼

(Optional)

Recovery Time:

30

(30-1440 Minutes)

Description:

(1-50 characters, optional)

OK

Cancel

(). "5".

tp-link ACS50 Wireless Controller

Save Config Logout

Redirect Page Web Authentication Onekey Online Remote Portal Free Authentication Policy Authentication Config

Authentication Parameters

☒ Authentication Aging

Aging Time: 5 (5-30 minutes)

Portal Authentication Port: 8080 (80, 1024-65535)

Save

, WNAM . "Authentication" "Free Authentication Policy" WNAM ().

tp-link ACS50 Wireless Controller

Save Config Logout

Redirect Page Web Authentication Onekey Online Remote Portal Free Authentication Policy Authentication Config

Free Authentication Policy

☒ Enable ☒ Disable ☒ Add ☒ Delete ☒ Search

☐	ID	Strategy Name	URL Address	Source IP Range	Destination IP Range	Source Port	Destination Port	Protocol	Description	Status	Operation
☐	1	dhcp client	---	---	---	68-68	67-67	UDP	---	Enabled	---
☐	2	dhcp server	---	---	---	67-67	68-68	UDP	---	Enabled	---
☐	3	dns client	---	---	---	---	53-53	UDP	---	Enabled	---
☐	4	dns server	---	---	---	53-53	---	UDP	---	Enabled	---
☐	5	WNAM	---	172.16.70.0/24	172.16.130.5/32	---	8080-8080	TCP	---	Enabled ☒	☒ ☒
☐	6	ac-pass	---	172.16.70.0/24	172.16.130.7/32	---	---	---	---	Enabled ☒	☒ ☒

Total 6 Items, 10 Per Page | Current 1/1 Page 1~6 Items | ☒ 1 ☒

Copyright © 2016 TP-Link Technologies Co., Ltd.

"Remote Portal" WNAM : <http://172.16.130.5:8080/cp/tplink>.

tp-link ACS50 Wireless Controller

Save Config Logout

Redirect Page Web Authentication Onekey Online Remote Portal Free Authentication Policy Authentication Config

Remote Portal

☒ Enable ☒ Disable ☒ Add ☒ Delete ☒ Search

☐	ID	Redirect Page	VLAN ID	Server Type	Non-sense Authentication	Description	Status	Operation
☐	1	1	---	Remote Authentication Server	Disabled ☒	WNAM	Enabled ☒	☒ ☒

Total 1 Items, 10 Per Page | Current 1/1 Page 1~1 Items | ☒ 1 ☒

- ▶ Status
- ▶ Network
- ▶ AP Control
- ▶ Radio
- ▶ Wireless
- ▼ Authentication
 - MAC Authentication
 - Portal Authentication
 - User Management
 - Authentication Server
- ▶ Link Backup
- ▶ System Tools

Copyright © 2016
TP-Link Technologies Co., Ltd.
All rights reserved.

- ▶ Authentication
 - MAC Authentication
 - Portal Authentication
 - User Management
 - Authentication Server

- ▶ Link Backup
- ▶ System Tools

Copyright © 2016
TP-Link Technologies Co., Ltd.
All rights reserved.

- Redirect Page
- Web Authentication
- Onekey Online
- Remote Portal
- Free Authentication Policy
- Authentication Config

Remote Portal



☒ Enable
 ☒ Disable
 ☒ Add
 ☒ Delete
 ☒ Search

☐	ID	Redirect Page	VLAN ID	Server Type	Non-sense Authentication	Description	Status	Operation
☐	1	1	---	Remote Authentication Server	Disabled	WNAM	Enabled	---

Status: ☒ On ☐ Off

Redirect Page: (1-50 English characters. Letters, digits, underscores or dashes are valid)

VLAN ID: (1-4094, optional)

Remote Portal Address:

(1-100 letters, digits or special characters)

Authentication Server Type: Remote Authentication Server

Authentication Server Group: WnamG

Free Authentication Timeout: Minutes (1-1440)

Success Redirect URL:

(Optional. Enter 1-120 letters, digits or special characters)

Fail redirect URL:

(Optional. Enter 1-120 letters, digits or special characters)

Non-sense Authentication: ☐ Enable ☒ Disable

Description: (1-50 characters, optional)

Note:

1. The remote portal address and the failure redirect URL will join the free authentication policy automatically and no manual configuration is needed.
2. If the remote authentication server is selected, and the server is configured with an online time duration for the users, then this time duration is the time that users can connect to the wireless network for free.

OK Cancel

WNAM (" " " ") "TP-Link EAP/CAP" IP- .