Huawei

1.3.1090 WNAM Huawei. Wi-Fi Huawei :

- AP2050, AP5030, AP4050, AP6050, AP6010 , FAT, ;
- FIT ( ) AC6005, AC6605.

WNAM "External Portal Server". Huawei (Agile Controller) .

WNAM , . "" " " , - Huawei, IP- , . " " " NetFlow" .

Huawei () . WNAM () RADIUS "", WNAM / UDP:2000 ( ).

:

- WNAM, UDP 1812 1813;
- WNAM , UDP 2000.

Firewall NAT, .

Huawei "" , - web-auth-server (GUI). , , .

!

AP5030DN FAT V200R006C10SPCa00. Web-, (RADIUS-) CLI. . . IP- WNAM: 172.16.130.5, RADIUS- 80.

```
#
authentication-profile name wnam-authentication-profile
 portal-access-profile wnam-portal-access-profile
 free-rule-template default_free_rule
 authentication-scheme radius
 accounting-scheme default
 radius-server wnam_radius
#
portal captive-bypass disable
#
radius-server template wnam_radius
 radius-server shared-key cipher %^%#Nl=Y8Wyh"ZWb:P(H`d)8>Nf1<Pio=2bWLA"Xn1A8%^%#
 radius-server authentication 172.16.130.5 1812 weight 80
 radius-server accounting 172.16.130.5 1813 weight 80
 radius-server hw-dhcp-option-format new
 radius-server hw-ap-info-format include-ap-ip
 calling-station-id mac-format hyphen-split mode2 uppercase
 radius-attribute check Session-Timeout
 radius-attribute check HW-Input-Committed-Information-Rate
 radius-attribute check HW-Output-Committed-Information-Rate
#
free-rule-template name default_free_rule
 free-rule 1 destination ip 172.16.130.5 mask 255.255.255.255
#
url-template name urlTemplate_0
 url http://172.16.130.5/cp/huawei
 url-parameter ap-ip AP-IP ap-mac AP-MAC redirect-url redirect-url ssid ssid
user-ipaddress user-ipaddress user-mac user-mac sysname sysname ac-ip AC-IP
 url-parameter mac-address format delimiter : normal
#
web-auth-server wnam-server
 server-ip 172.16.130.5
 port 50200
 url http://172.16.130.5/cp/huawei
 url-template urlTemplate_0
 server-source ip-address ____mgmt__
#
portal-access-profile name wnam-portal-access-profile
 web-auth-server wnam-server layer3
#
aaa
 authentication-scheme default
 authentication-scheme radius
```

```
 authentication-mode radius
 authorization-scheme default
 accounting-scheme default
 accounting-mode radius
 accounting realtime 5
 accounting start-fail online
 domain default
 domain default_admin
#
wlan
 traffic-profile name default
 security-profile name default
 security-profile name default-mesh
 security wpa2 psk pass-phrase %^%#U/o>@VZq@K@@r-BP_rFX!&H3Gc`_{HZ<3|*AE(WR%^%#
aes
 ssid-profile name default
 ssid HUAWEI
 vap-profile name default
 authentication-profile wnam-authentication-profile
 mesh-handover-profile name default
 mesh-profile name default
 country-code RU
 air-scan-profile name default
 rrm-profile name default
 radio-2g-profile name default
 radio-5g-profile name default
 wids
#
interface Wlan-Radio0/0/0
 vap-profile default wlan 1
#
```

:


```
portal captive-bypass enable
```


, Apple - , ( ) , . , , . , (, https-) , .


CNA :


```
undo portal captive-bypass enable
```


, :



Wireless LAN
AP5030DN
Monitoring
Wizard
Configuration
Maintenance
Save
Console
admin
Interface
IP Service
WLAN Service
Basic Config
WLAN Config
Profile
Security
Proxied Device
IGMP-Snooping
Radio0
Radio1
VAP Configuration
default
SSID Profile [defa...]
Security Profile [defa...]
Traffic Profile [defa...]
Authentication ... [wna...]
STA Blacklist And Whitelist ...
Radio Management
Mesh
WLAN Location
Authentication Profile : wnam-authentication-p
Display Reference
Prevent authentication overwrite : Disable
Security character string separator : none found
User group : none found
Authorization VLAN ID before authentication : none found
Authorization VLAN ID upon authentication failure : none found
Binding Profile
802.1X Profile : none found
Portal Profile : wnam-portal-access-profile
MAC Authentication Profile : mac_access_profile
Authentication-free Rule Profile : default_free_rule
RADIUS Server Profile : wnam_radius
HWTACACS Server Profile : none found
Authentication Scheme : radius
Authorization Scheme : none found
Accounting Scheme : default
Service scheme : none found
Apply



Wireless LAN
AP5030DN
Monitoring
Wizard
Configuration
Maintenance
Save
Console
admin
Interface
IP Service
WLAN Service
Basic Config
WLAN Config
Profile
Security
Proxied Device
IGMP-Snooping
Profile Management
Wireless Service
VAP Profile
default
SSID Profil... [defa...]
Security Pr... [defa...]
Traffic Profil... [defa...]
Authenticati... [wna...]
STA Blacklist And Whiteli...
SSID Profile
Security Profile
Traffic Profile
Authentication Profile
802.1X Profile
Portal Profile
portal_access_profile
wnam-portal-access-profil...
MAC Authentication Profile
Authentication-free Rule Prof...
Authentication Scheme
Authorization Scheme
Accounting Scheme
Portal Profile : wnam-portal-access-profile
Display Reference
Portal authentication : Built-in portal server External portal server
Portal server : wnam-server
Authentication mode : Layer 2 authentication Layer 3 authentication
Source authentication network segment/mask : - none -
Source Authentication Network Seg... Mask
No data.


Wireless LAN
AP5030DN
Monitoring
Wizard
Configuration
Maintenance
Save
Console
admin
Interface
IP Service
WLAN Service
Security
AAA
User Group
ACL
WIDS
SSL
PKI
Security Defense
Proxied Device
Authentication Profile
Service Scheme
External Portal Server
Built-In Portal Server
RADIUS
HWTACACS
Local User
Advanced
Authentication Profile List
mac_authen_profile
dot1x_authen_profile
portal_authen_profile
macportal_authen_profile
wnam-authentication-profile
802.1X Profile
Portal Profile [wna...]
MAC Authentic... [mac...]
Authentication-f... [defa...]
RADIUS Serve... [wna...]
HWTACACS Server Profile
Authentication ... [radiu...]
Authorization Scheme
Accounting Sc... [defa...]
Service Scheme
Authentication Scheme : radius
Display Reference
Create
First authentication : RADIUS authentication
Second authentication : Not configured
Third authentication : Not configured
Fourth authentication : Not configured
Apply


Wireless LAN
AP5030DN
Monitoring
Wizard
Configuration
Maintenance
Save
Console
admin
中文
Interface
IP Service
WLAN Service
Security
AAA
User Group
ACL
WIDS
SSL
PKI
Security Defense
Proxied Device
Authentication Profile
Service Scheme
External Portal Server
Built-In Portal Server
RADIUS
HWTACACS
Local User
Advanced
Maximum number of STAs : 64
Apply
Portal Authentication Server List
Create
Delete
Refresh
Server Name
Server Name
URL
Packet Port Number
50200
wnam-server
http://172.16.130.5/cp/huawei
50200
10
Total 2 record(s)
1


Wireless LAN
AP5030DN
Monitoring
Wizard
Configuration
Maintenance
Save
Console
Interface
IP Service
WLAN Service
Security
AAA
User Group
ACL
WIDS
SSL
PKI
Security Defense
Proxied Device
IGMP-Snooping
Security > AAA > External Portal Server > Modify Authentication Server
*Server name :
wnam-server
*Server IP :
Server IP
172.16.130.5
Shared key :
Confirm shared key :
Packet port number :
50200
*URL :
http://172.16.130.5 /cp/hu
URL configuration result :
http://172.16.130.5/cp/huawei?AP-IP=&AP-MAC=&redirect-url=&ssid=&user-ipaddress=&user-mac=&sysname=
URL Option Settings
Redirection Setting
User access URL :
User MAC :
User IP :
System name :
AP-IP :
AP-MAC :
SSID :
MAC Address
MAC address format :
normal
*Separator :
:
URL Encrypt
Encrypted parameter name :
Encryption vector name :
Encryption key :
Confirm encryption key :
Server Detection Configuration
Portal server detection :
OFF
OK
Cancel





WNAM .

:

```
radius-attribute check Session-Timeout
radius-attribute check HW-Input-Committed-Information-Rate
radius-attribute check HW-Output-Committed-Information-Rate
```

, RADIUS-Accept WNAM . , (rx/tx) "" . , , , . , .

Wi-Fi - WNAM :

```
21:08:11.706 DEBUG [c.n.w.web.cp.CaptivePortalController:544] - CP huawei
redirect: mac=4C:57:CA:XX:XX:XX, ip=172.16.130.154, ap=d4:c8:b0:15:1d:40
[HUAWEI], server=Huawei, 192.168.0.5
21:08:11.722 DEBUG [c.n.w.web.cp.CaptivePortalController:1661] -
processAuthRequest HUAWEI: username=4C:57:CA:XX:XX:XX, ip=172.16.130.154,
server=Huawei, site_id=3, dst='http://www.ru/'
21:08:11.722 DEBUG [c.n.w.web.cp.CaptivePortalController:1804] -
processRedirectRequestCi mac=4C:57:CA:XX:XX:XX, method=FORM,
formName=58addf80bd045a2fa888c7a6, redirectUrl=http://www.ru/, key=33f0eb37-ee12-
4572-ad58-10a1c237de00
21:08:13.053 DEBUG [c.n.w.web.cp.CaptivePortalController:1530] - RedirectCi
login: site_id=3, username=4C:57:CA:2C:0F:4C, dst='http://www.ru/',
dst_extra='null'
21:08:13.053 DEBUG [c.n.w.web.cp.CaptivePortalController:2102] - loginAtNasCi
HUAWEI mac=4C:57:CA:XX:XX:XX, ip=172.16.130.154, server=Huawei, dst='http://www.
ru/'
21:08:13.057 DEBUG [com.netams.wnam.web.cp.Huawei:85] - backToHuawei login
len=439, server='172.16.130.75', username=4C:57:XX:XX:XX:XX, password=password,
dst='http://www.ru/'
21:08:13.079 INFO [WnamRadius:522] - AUTH for new session
ID=Huawei000000000000019e7f4f000019-2c0f4c, request MAC=4C:57:CA:XX:XX:XX,
IP=172.16.130.154, cust_clientid=iSE
21:08:13.112 INFO [WnamRadius:683] - ACCT Start new session
ID=Huawei000000000000019e7f4f000019-2c0f4c, MAC=4C:57:CA:XX:XX:XX, IP=172.
16.130.154, NAS=172.16.130.75
21:13:13.124 INFO [WnamRadius:683] - ACCT Interim-Update existing
(Huawei000000000000019e7f4f000019-2c0f4c) session
ID=Huawei000000000000019e7f4f000019-2c0f4c, MAC=4C:57:CA:XX:XX:XX, IP=172.
16.130.154, NAS=172.16.130.75
21:13:13.652 INFO [WnamRadius:683] - ACCT Stop existing
(Huawei000000000000019e7f4f000019-2c0f4c) session
ID=Huawei000000000000019e7f4f000019-2c0f4c, MAC=4C:57:CA:XX:XX:XX, IP=172.
16.130.154, NAS=172.16.130.75
```

Huawei .